

Pocketbook (model 301, 301+, 360) firmware update instruction.

CAUTION! Updating firmware is important operation regarding changes of main software of the PocketBook. In case of misuse firmware may be damaged, and that can lead to device becoming unusable. In this case device should be admitted to the service centre. Please complete update procedure following strictly the steps described in this instruction.

Latest version of software for your device is available at WWW.GREENREADER.CO.UK website. To perform update operation you will need SD memory card (for PockedBook 360 — MicroSD).

- 1.Copy image file of the firmware (the file name is SWUPDATE.BIN) into the root directory of the SD-card.**
- 2.Attach power supply to the PocketBook (charging device or your computer, using USB-cable). During the entire update process the device must be attached to power supply.**
- 3.Turn off the PocketBook.**
- 4.For PocketBook 301, 301+: please turn on the device while holding «+» button on the right side of the book. For PocketBook 360: please turn on the device while holding central key and upper browsing button at the same time. Release the power button and then you can release other buttons only after the message "Firmware update" appears on top of the screen.**
- 5.Update program will perform firmware image file verification. If the check is successful, the message "Press center key to start update" will appear.**
- 6.Now press the central key. Firmware update will take about 2 minutes. If the update was successful, the screen will display a message "Update OK. Now please reset the device"**
- 7.For Pocketbook 301: please press the "Reset" button on rear panel of the device. Pocketbook 301+ and PocketBook 360 will reboot automatically.**
- 8.Turn off the device. Please verify that latest version of the firmware is installed ("Settings" - "Device Info" – "Firmware version").**
- 9.You can copy updated games and other accessoires from the archive with updated firmware into the „Games" folder of the device. Dictionaries can be copied the same way into the system/dictionaries folder (during the firmware update process the content of device built-in memory and SD-card is preserved).**

After the update process is finished you can delete SWUPDATE.BIN file from the SD-card.